



L1 = 4,7 mH / Copper Wire CUL \varnothing 1,4 mm / air
 L2 = 0,68 mH / Copper Wire CUL \varnothing 1,0 mm / air
 L3 = 5,6 mH / Copper Wire CUL \varnothing 1,0 mm / air
 L4 = 0,33 mH / Copper Wire CUL \varnothing 0,7 mm air

C1 = 150 MF / bipolar-capacitor / 50 Vac
 C2 = 6,8 MF / bipolar-Capacitor / 50 Vac
 C3 = 68 MF / bipolar-capacitor / 50 Vac
 C4 = 4,7 MF / foil-capacitor (MKP)

R1 = 1,5 Ohm / 4 W
 R2 = 5,6 Ohm / 4 W
 R3 = 0,75 Ohm / 10 W
 R4 = 15 Ohm / 4 W
 R5 = 2,7 Ohm / 4 W - metaloxid

WO = ETON 8-800/37 HEX / 8 Ohm
 MD = ETON 5-880/25 HEX / 8 Ohm
 TW = ETON 19 SD 1 / 8 Ohm

BR = BR/HP70 95 mm lang

| | | | | | | | |
|---|--|--|--|----------|------|-----------------|-----------|
| ETON Deutschland Electro Acoustic-GMBH Pfaffenweg 21, D-89231 Neu-Ulm Germany | | | | | | Scale: | |
| | | | | | | Material: | |
| | | | | Date | Name | ETON 8.2 | |
| | | | | 24.11.03 | Va | | |
| | | | | | | | |
| | | | | | | Art. No. | Crossover |
| | | | | | | | |